



USER MANUAL



The introductory information in this document may be changed for product improvement without prior notice. We reserve the right of final explanation and revision.



Godrej & Boyce Mfg. Co. Ltd.

Godrej Security Solutions

Regd. Office: Plant No. 17, Pirojshanagar, Vikhroli, Mumbai - 400 079.


Toll-freel: 1800 200 9955 | Email: secure@godrej.com

Visit: www.godrejsecure.com

In view of the Godrej Policy of continuous development and improvement, the dimensions as seen on the flyer of the product may not match with the actual product. The colour combinations of the products as seen on this flyer may vary and not match with the actual colour of the product due to printing limitations. Prices may be changed without prior notice.


An ISO 9001, ISO 140001 & OHSAS 18001 \mid Products Marketed and Serviced By Godrej & Boyce Mfg. Co. Ltd.

Name and functions of each part




NO.	Part Name	Description
1	LCD Screen	4.3 inch TFT LCD screen
2	Power Cab e	AC power cab e
3	Monitor utton 2	utton for monitoring camera 2
4	Door Re ease utton	utton for re easing door oc
5	MIC	Microphone
6	Monitor utton 1	utton for monitoring camera 1
	Ta utton	utton for ta ing with visitor
	Power Indicator	Red ed
	Menu utton	
10	Up utton	
11	Down utton	
12	E it utton	
13	Power Switch	
14	DC Power	14.5V DC supp y
15	Video Input	Interface for door station 1/ door station 2
16	Spea er	

Wiring diagram



Insta ation


Standard monitor insta ation height is about 1,500mm where screen center is at eye eve in this case, wa -hanging meta center is 1,450mm above ground eve .



- 1 Remove wa -hanger brac et behind monitor 2 Insta wa -hanger
- brac et
- 3 Connect wires to bac termina of monitor, referring to connection diagram
- 4 Hang monitor on wa hanging, and monitor on wa -hanger brac et
- 5 P ug monitor s power p ug into power soc et

Operation description


The de nition of buttons are as be ow:



Features and functions

- Features
- 4.3 co or indoor monitor
- Support 2 door stations
- rightness, co or and contrast ad ustab e
- Ringtone vo ume ad ustab e
- Hands-free
- PAL/NTSC convertib e
- Do not disturb function
- Main functions
- OSD menu
- Door oc re ease
- Monitoring and ta ing with a visitor
- Support both AC and DC power input

Pac ing contents



Category	Speci cation	
Input power	AC: 100V ~ 240V, 50Hz/60Hz DC: 14.5V±0.5V	
Power consumption	Ma: W, standby: 1.5W	
TFT LCD	4.3 inch digita TFT LCD	
LCD reso ution	4 0 RG 2 2	
Connection with camera	Support two 4-wire outdoor stations	
Dimensions mm	162 W * 2 H *20. D	

NOTES